


# Amplification Chart

## V5.3

Distribution Date  
May 10, 2022





# Adamson Amplification Chart

## Maximum Cabinet Count per Amplifier

- The following charts presume amplifiers running on 208 / 230 V for maximum performance. Lower mains voltage can reduce available headroom.
- Maximum recommended speaker cable length per circuit 100 ft / 30 m, with minimum AWG 11 / 4 mm<sup>2</sup> wires. Extended length or reduced section can reduce performance.

Family	Product	Channels Used	PLM20K44 / D200:4		PLM12K44 / D120:4	
			# Per Circuit	# Per Amp	# Per Circuit	# Per Amp
E-Series	E15	4	3	3	N/A	N/A
	E12	4	3	3	N/A	N/A
	E219	2	2	3*	N/A	N/A
	E119	1	2	6*	N/A	N/A
S-Series	S10 / S10n	2	4	8	4	8
	S119	1	2	8	2	4
	S7	2	4	8	4	8
	S118	1	4	16	4	12
	S10p	2	4	8	4	8
	S7p (Bi-Amped)	2	4	8	4	8
	S7p (Passive)	1	3	12	3	12
IS-Series	IS10 / IS10n	2	4	8	4	8
	IS119	1	2	8	2	4
	IS7	2	6	12	6	12
	IS118	1	4	16	4	12
	IS10p	2	4	8	4	8
	IS7p	2	4	8	4	8
	IS7px	1	3	12	3	12
	IS5c	1	8	32	8	32
	IS213	1	2	6*	2	4
	IS219	1	1	3*	1	2

\* The use of eight SD19 drivers or IS213 per amp requires 208 / 230 V mains voltage operation. Depending on source material it may reduce headroom and will increase thermal load. It is not recommended for sustained maximum output applications. Please contact Adamson support in case of any questions.



# Adamson Amplification Chart

## Maximum Cabinet Count per Amplifier

Family	Product	Channels Used	PLM20K44 / D200:4		PLM12K44 / D120:4	
			# Per Circuit	# Per Amp	# Per Circuit	# Per Amp
Point Series	P8P	1	4	16	4	16
	P12A	2	3	6	3	6
	P12P	1	3	12	3	10
	P15A	2	3	6	3	6
	P15P	1	3	12	3	10
	P115P + P8P	1	1	4	1	4
	P115A	1	4	16	3	12
	P215	1	2	8	2	6
	A218	1	2	6	2	4
Point Concentric Series	PC5	1	2	8	2	8
	PC6	1	3	12	3	12
	PC8	1	2	8	2	8
	PC10	1	2	8	2	8
	PC12	1	2	8	2	8
M-Series	M15A	2	3	6	3	6
	M15P	1	3	12	3	10
	M12A	2	3	6	3	6
	M12P	1	3	12	3	10
	M215	2	2	4	2	4
	M212	2	2	4	2	4
Legacy Products	E218	2	3	6	N/A	N/A
	Y18	4	2	2	2	2
	Y10 / Y10K	4	4	4	4	4
	T21	2	1	2	N/A	N/A
	SX18A	3	4	4	4	4
	SX18P	2	4	8	4	8
	MTX / MTXW	2	8	16	8	12
	MTB	1	2	8	2	6
	SPK / SPKW	3	4	4	4	4
	SPB	1	2	6	2	5



# Adamson Amplification Chart

## Maximum Cabinet Count per Amplifier

Family	Product	Channels Used	D80:4		PLM 5K44		D40:4	
			# Per Circuit	# Per Amp	# Per Circuit	# Per Amp	# Per Circuit	# Per Amp
E-Series	E15	4	N/A	N/A	N/A	N/A	N/A	N/A
	E12	4	N/A	N/A	N/A	N/A	N/A	N/A
	E219	2	N/A	N/A	N/A	N/A	N/A	N/A
	E119	1	N/A	N/A	N/A	N/A	N/A	N/A
S-Series	S10 / S10n	2	4	5	N/A	N/A	N/A	N/A
	S119	1	1	3	N/A	N/A	N/A	N/A
	S7	2	4	6	2	4	2	3
	S118	1	2	8	1	4	1	4
	S10p	2	4	5	1	2	1	2
	S7p (Bi-Amped)	2	4	6	2	4	2	3
	S7p (Passive)	1	3	8	1	4	1	4
IS-Series	IS10 / IS10n	2	4	5	1	2	1	2
	IS119	1	1	3	N/A	N/A	N/A	N/A
	IS7	2	6	8	2**	4**	2**	4**
	IS118	1	2	8	1	4	1	4
	IS10p	2	3	4	1	2	1	2
	IS7p	2	4	8	2	4	2	3
	IS7px	1	3	8	1	4	1	4
	IS5c	1	8	32	5	20	4	16
	IS213	1	2	2	N/A	N/A	N/A	N/A
	IS219	1	N/A	N/A	N/A	N/A	N/A	N/A

\*\* LF headroom reduced by 2 dB. Only recommended for fill applications.



# Adamson Amplification Chart

## Maximum Cabinet Count per Amplifier

Family	Product	Channels Used	D80:4		PLM 5K44		D40:4	
			# Per Circuit	# Per Amp	# Per Circuit	# Per Amp	# Per Circuit	# Per Amp
Point Series	P8P	1	4	14	2	8	2	6
	P12A	2	3	6	1	2	1	2
	P12P	1	2	8	1	4	1	3
	P15A	2	3	6	1	2	1	2
	P15P	1	2	8	1	4	1	3
	P115P + P8P	1	1	4	1	4	1	3
	P115A	1	3	8	1	4	1	4
	P215	1	2	4	N/A	N/A	N/A	N/A
	A218	1	2	3	N/A	N/A	N/A	N/A
Point Concentric Series	PC5	1	2	8	2	8	2	8
	PC6	1	3	12	3	12	3	12
	PC8	1	2	8	1	4	1	4
	PC10	1	2	8	1	4	1	4
	PC12	1	2	8	1	4	1	4
M-Series	M15A	2	3	6	1	2	1	2
	M15P	1	3	6	1	4	1	3
	M12A	2	3	6	1	2	1	2
	M12P	1	3	6	1	4	1	3
	M215	2	2	3	N/A	N/A	N/A	N/A
	M212	2	2	3	N/A	N/A	N/A	N/A
Legacy Products	E218	2	N/A	N/A	N/A	N/A	N/A	N/A
	Y18	4	1	1	N/A	N/A	N/A	N/A
	Y10 / Y10K	4	2	2	N/A	N/A	N/A	N/A
	T21	2	N/A	N/A	N/A	N/A	N/A	N/A
	SX18A	3	3	3	2	2	1	1
	SX18P	2	3	4	1	2	1	2
	MTX / MTXW	2	8	12	3	6	3	6
	MTB	1	2	4	N/A	N/A	N/A	N/A
	SPK / SPKW	3	4	4	2	2	2	2
	SPB	1	2	3	N/A	N/A	N/A	N/A



# Adamson Amplification Chart

## Maximum Cabinet Count per Amplifier

Family	Product	Channels Used	PLM 10000Q		PLM 20000Q		IPD / IPX 2400	
			# Per Circuit	# Per Amp	# Per Circuit	# Per Amp	# Per Circuit	# Per Amp
E-Series	E15	4	N/A	N/A	3	3	N/A	N/A
	E12	4	N/A	N/A	3	3	N/A	N/A
	E219	2	N/A	N/A	2	3*	N/A	N/A
	E119	1	N/A	N/A	2	6*	N/A	N/A
S-Series	S10 / S10n	2	3	6***	4	8***	N/A	N/A
	S119	1	1	4	2	8	N/A	N/A
	S7	2	3	6***	4	8***	N/A	N/A
	S118	1	3	12	4	16	N/A	N/A
	S10p	2	3	6	4	8	N/A	N/A
	S7p (BiAmp)	2	3	6	4	8	N/A	N/A
	S7p (Passive)	1	3	10	3	12	N/A	N/A
IS-Series	IS10	2	3	6***	4	8***	N/A	N/A
	IS119	1	1	4	2	8	N/A	N/A
	IS7	2	N/A	N/A	6	12***	N/A	N/A
	IS118	1	3	12	2	8	N/A	N/A
	IS10p	2	3	6	4	8	N/A	N/A
	IS7p	2	3	6	4	8	N/A	N/A
	IS7px	1	3	10	3	12	N/A	N/A
	IS5c	1	8	32	8	32	3	6
	IS213	1	N/A	N/A	2	6*	N/A	N/A
	IS219	1	N/A	N/A	1	3*	N/A	N/A

\* The use of eight SD19 drivers or IS213 per amp requires 208 / 230 V mains voltage operation. Depending on source material it may reduce headroom and will increase thermal load. It is not recommended for sustained maximum output applications. Please contact Adamson support in case of any questions.

\*\*\* Only one processing module available. All cabinets are driven from the same input signal.



# Adamson Amplification Chart

## Maximum Cabinet Count per Amplifier

Family	Product	Channels Used	PLM 10000Q		PLM 20000Q		IPD / IPX 2400	
			# Per Circuit	# Per Amp	# Per Circuit	# Per Amp	# Per Circuit	# Per Amp
Point Series	P8P	1	4	16	4	16	1	2
	P12A	2	3	6	3	6	1	1
	P12P	1	3	10	3	12	1	2
	P15A	2	3	6	3	6	1	1
	P15P	1	3	10	3	12	1	2
	P115P + P8P	1	1	4	1	4	1	2
	P115A	1	3	12	4	16	1	2
	P215	1	1	4	2	8	N/A	N/A
	A218	1	1	4	2	6	N/A	N/A
Point Concentric Series	PC5	1	2	8	2	8	1	2
	PC6	1	3	12	3	12	2	4
	PC8	1	2	8	2	8	1	2
	PC10	1	2	8	2	8	1	2
	PC12	1	2	8	2	8	1	2
M-Series	M15A	2	2	4	3	6	N/A	N/A
	M15P	1	2	8	3	12	N/A	N/A
	M12A	2	2	4	3	6	N/A	N/A
	M12P	1	2	8	3	12	N/A	N/A
	M215	2	1	2	2	4	N/A	N/A
	M212	2	1	2	2	4	N/A	N/A
Legacy Products	E218	2	N/A	N/A	3	6	N/A	N/A
	Y18	4	2	2	2	2	N/A	N/A
	Y10 / Y10K	4	4	4	4	4	N/A	N/A
	T21	2	N/A	N/A	1	2	N/A	N/A
	SX18A	3	3	3	4	4	N/A	N/A
	SX18P	2	3	6	4	8	N/A	N/A
	MTX / MTXW	2	6	12	8	16	N/A	N/A
	MTB	1	1	4	2	8	N/A	N/A
	SPK / SPKW	3	4	4	4	4	N/A	N/A
	SPB	1	1	4	2	8	N/A	N/A

# Adamson Amplification Chart



## Version History

### V5.3

- Added IS5c
- Added IS213
- Adjusted the name of IPD to IPD / IPX
- Added channels used and # per circuit for IS219 on PLM+ 12k44

### V5.2

- Added Version History
- Corrected IS219 channels used and # per circuit
- PLM5k44 and D40:4 support for (I)S118, (I)S7, (I)S7p and (I)S10p
- Corrected number of (I)S118 per D40

### V5.1

- Minor layout changes
- Added title page including version number and release date
- Moved E218 to the legacy section
- Updated note for SD19 drivers

### V5.0

- Minor layout changes
- Added S7p, S10p and IS219
- Moved Metrix and Spektrix to the legacy section
- Changed note for SD19 drivers
- Changed naming of retired section to legacy section

### V1.0

- First version of this document replacing all other places information on amplifier capacity was published before



© 2021 Adamson Systems Engineering. All rights reserved.

No part of this publication may be reproduced or transmitted in any form or by any means without the written permission of the publisher.